

2. Übersicht

Kurzbezeichnung														
Foto														
Bestellnummer	4PP015.0420-01	4PP015.0420-36	4PP015.C420-01	4PP015.E420-01	4PP015.E420-101	4PP015.C420-36	4PP015.E420-36	4P0420.00-490	4PP035.0300-01	4PP035.0300-36	4PP035.E300-01	4PP035.E300-36	4PP035.E300-136	4P3040.01-490
Seite	24	44	24	44	77	102	122	102	122	155				
LCD-Display														
4 x 20 Zeichen	✓		✓		✓	-	-	-						
160 x 80 Bildpunkte	-		-		-	✓	✓	✓						
5,7" QVGA	-		-		-	-	-	-	✓					✓
Zeichensatz														
Englisch / Katakana	✓	-	-	-	-	✓	-	-	-	-	-	-	-	-
Englisch / Kyрилisch	-	✓	-	-	✓	-	-	-	-	-	-	-	-	-
Englisch / Europäisch	-	-	✓	✓	-	✓	-	-	-	-	-	-	-	-
Europäisch / Kyрилisch	-	-	-	-	-	-	-	✓	✓	✓	✓	✓	✓	-
Tasten														
insgesamt	16	26	26	26	34	16	26	26	40	40	40	40	40	40
mit Tasten-LED	12	10	10	10	17	12	10	10	16	16	16	16	16	16
mit Einschubstreifen	10	10	10	10	17	10	10	10	16	16	16	16	16	16
Ein-/Ausgänge														
Digitale Eingänge	16	8	16	8	10	16	8	16	8	10	10	10	10	10
Digitale Ausgänge	16	8	16	8	8	16	8	16	8	10	10	10	10	10
Analoge Eingänge	-	4	-	4	-	-	4	-	4	-	-	-	-	-
Analoge Ausgänge	-	4	-	4	-	-	4	-	4	-	-	-	-	-
Befehlszykluszeit														
0,8 µs		✓			-	✓			-					-
0,5 µs		-			✓	-			✓					✓
Speicher (SRAM / SystemPROM)														
300 kByte / 448 kByte		✓			-	✓			-					-
700 kByte / 600 kByte		-			✓	-			-					✓
FlashPROM														
1,0 MByte	✓	-	✓	-	-	✓	-	✓	-	-	-	-	-	-
1,4 MByte	-	-	-	✓	✓	-	-	-	-	-	-	-	-	✓
1,9 MByte	-	✓	-	-	-	-	-	-	✓	-	-	-	-	-
Steckplätze für ...														
B&R 2003 Anpassungsmodule		-			6	-			6					6
B&R 2005 Kommunikationsmodule		-			1	-			-					1

Tabelle 3: Power Panel Übersicht