## **SIEMENS**

## **Data sheet**

6ES7314-6CG03-0AB0



\*\*\*Spare part\*\*\* SIMATIC S7-300, CPU 314C-2 DP Compact CPU with MPI, 24 DI/16 DO, 4 AI, 2 AO, 1 Pt100, 4 high-speed counters (60 kHz), integrated DP interface, Integr. power supply 24 V DC, Work memory 96 KB, Front connector (2x 40-pole) and Micro Memory Card required

General information	
Engineering with	
Programming package	STEP 7 V5.3 SP2 or higher with HW update
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	20.4 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines (recommendation)	Miniature circuit breaker, type C; min. 2 A; miniature circuit breaker type B, min. 4 A
Load voltage L+	
<ul> <li>Rated value (DC)</li> </ul>	24 V
<ul> <li>permissible range, lower limit (DC)</li> </ul>	20.4 V
<ul> <li>permissible range, upper limit (DC)</li> </ul>	28.8 V
Digital inputs	
— Rated value (DC)	24 V
<ul> <li>Reverse polarity protection</li> </ul>	Yes
Digital outputs	
— Rated value (DC)	24 V
<ul> <li>Reverse polarity protection</li> </ul>	No
Analog outputs	
— Rated value (DC)	24 V
Reverse polarity protection	Yes
Input current	
Current consumption (rated value)	1 000 mA
Current consumption (in no-load operation), typ.	150 mA
Inrush current, typ.	11 A
l²t	0.7 A <sup>2</sup> ·s
Digital inputs	
from load voltage L+ (without load), max.	70 mA
Digital outputs	
from load voltage L+, max.	100 mA
Power loss	
Power loss, typ.	14 W
Memory	
Work memory	
• integrated	96 kbyte
<ul><li>expandable</li></ul>	No

Load memory	
Load memory	Yes
<ul><li>Plug-in (MMC)</li><li>Plug-in (MMC), max.</li></ul>	8 Mbyte
Data management on MMC (after last)	10 y
programming), min.	10 y
Backup	
• present	Yes; Guaranteed by MMC (maintenance-free)
<ul><li>without battery</li></ul>	Yes; Program and data
CPU processing times	
for bit operations, typ.	0.1 μs
for word operations, typ.	0.2 µs
for fixed point arithmetic, typ.	2 µs
for floating point arithmetic, typ.	3 µs
CPU-blocks	
Number of blocks (total)	1 024; (DBs, FCs, FBs); the maximum number of loadable blocks can
Number of blocks (total)	be reduced by the MMC used.
DB	
Number, max.	511; Number range: 1 to 511
• Size, max.	16 kbyte
FB	
Number, max.	1 024; Number range: 0 to 2047
• Size, max.	16 kbyte
FC	
Number, max.	1 024; Number range: 0 to 2047
• Size, max.	16 kbyte
OB	
• Size, max.	16 kbyte
<ul> <li>Number of free cycle OBs</li> </ul>	1; OB 1
<ul> <li>Number of time alarm OBs</li> </ul>	1; OB 10
<ul> <li>Number of delay alarm OBs</li> </ul>	1; OB 20
<ul> <li>Number of cyclic interrupt OBs</li> </ul>	1; OB 35
<ul> <li>Number of process alarm OBs</li> </ul>	1; OB 40
<ul> <li>Number of DPV1 alarm OBs</li> </ul>	3; OB 55, 56, 57
<ul> <li>Number of startup OBs</li> </ul>	1; OB 100
<ul> <li>Number of asynchronous error OBs</li> </ul>	5; OB 80, 82, 85, 86, 87
<ul> <li>Number of synchronous error OBs</li> </ul>	2; OB 121, 122
Nesting depth	
<ul> <li>per priority class</li> </ul>	8
<ul> <li>additional within an error OB</li> </ul>	4
Counters, timers and their retentivity	
S7 counter	
Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit	255
Counting range	
— lower limit	0
— upper limit	999
IEC counter	
• present	Yes
• Type	SFB
Number	Unlimited (limited only by RAM capacity)
S7 times	
Number	256
Retentivity	
	Yes

— upper limit	255
— preset	No retentivity
Time range	
— lower limit	10 ms
— upper limit	9 990 s
IEC timer	
<ul><li>present</li></ul>	Yes
• Type	SFB
<ul><li>Number</li></ul>	Unlimited (limited only by RAM capacity)
Data areas and their retentivity	
retentive data area in total	all, max. 64 KB
Flag	
Number, max.	256 byte
Retentivity available	Yes; MB 0 to MB 255
Retentivity preset	MB 0 to MB 15
Number of clock memories	8; 1 memory byte
Data blocks	e, i monety byte
Retentivity adjustable	Yes; via non-retain property on DB
Retentivity adjustable     Retentivity preset	Yes
Local data	160
• per priority class, max.	510 byte
	5 to byte
Address area	
I/O address area	
<ul><li>Inputs</li></ul>	1 kbyte
Outputs	1 kbyte
of which distributed	
— Inputs	979 byte
— Outputs	986 byte
Process image	
• Inputs	128 byte
<ul><li>Outputs</li></ul>	128 byte
Default addresses of the integrated channels	
<ul><li>— Digital inputs</li></ul>	124.0 to 126.7
<ul><li>— Digital outputs</li></ul>	124.0 to 125.7
<ul> <li>Analog inputs</li> </ul>	752 to 761
<ul> <li>Analog outputs</li> </ul>	752 to 755
Digital channels	
• Inputs	7 856
— of which central	1 016
<ul> <li>Outputs</li> </ul>	7 904
— of which central	1 008
Analog channels	
• Inputs	494
— of which central	253
Outputs	495
of which central	250
Hardware configuration	
	3
Number of expansion units, max.	J
Number of DP masters	4
• integrated	1
• via CP	4
Number of operable FMs and CPs (recommended)	
• FM	8
• CP, PtP	8
◆ CP, LAN	10
Rack	
• Racks, max.	4
<ul> <li>Modules per rack, max.</li> </ul>	8; In rack 3 max. 7

Time of day	
Clock	
Hardware clock (real-time)	Yes
retentive and synchronizable	Yes
Backup time	6 wk; At 40 °C ambient temperature
Deviation per day, max.	10 s
Operating hours counter	
• Number	1
Range of values	0 to 2^31 hours (when using SFC 101)
Granularity	1 h
retentive	Yes; Must be restarted at each restart
Clock synchronization	
• supported	Yes
• to MPI, master	Yes
• to MPI, slave	Yes
• to DP, master	Yes; With DP slave only slave clock
• to DP, slave	Yes
• in AS, master	Yes
Digital inputs	
Number of digital inputs	24
of which inputs usable for technological functions	16
integrated channels (DI)	24
Input characteristic curve in accordance with IEC 61131,	Yes
type 1	103
Number of simultaneously controllable inputs	
horizontal installation	
— up to 40 °C, max.	24
— up to 60 °C, max.	12
vertical installation	
— up to 40 °C, max.	12
Input voltage	
<ul><li>Rated value (DC)</li></ul>	24 V
• for signal "0"	-3 to +5V
• for signal "1"	+15 to +30 V
Input current	
• for signal "1", typ.	9 mA
Input delay (for rated value of input voltage)	
for standard inputs	
<ul><li>parameterizable</li></ul>	Yes; 0.1 / 0.3 / 3 / 15 ms
<ul> <li>Rated value</li> </ul>	3 ms
for technological functions	
— at "0" to "1", max.	8 µs
Cable length	
<ul><li>shielded, max.</li></ul>	1 000 m; 50 m for technological functions
• unshielded, max.	600 m; for technological functions: No
for technological functions	
— shielded, max.	50 m
— unshielded, max.	not allowed
Digital outputs	
Number of digital outputs	16
of which high-speed outputs	4
integrated channels (DO)	16
Short-circuit protection	Yes; Clocked electronically
Response threshold, typ.	1 A
Limitation of inductive shutdown voltage to	L+ (-48 V)
Controlling a digital input	Yes
Switching capacity of the outputs	
on lamp load, max.	5 W

Load resistance range	
Load resistance range  • lower limit	48 Ω
	4ο Ω 4 kΩ
upper limit  Output valtege	4 K12
Output voltage	1+(08)/\
for signal "1", min.  Output current	L+ (-0.8 V)
·	500 mA
• for signal "1" rated value	
• for signal "1" permissible range, min.	5 mA
• for signal "1" permissible range, max.	0.6 A
• for signal "1" minimum load current	5 mA
• for signal "0" residual current, max.	0.5 mA
Parallel switching of two outputs	Ma
• for uprating	No Voc
for redundant control of a load	Yes
Switching frequency	400 11-
with resistive load, max.	100 Hz
with inductive load, max.	0.5 Hz
on lamp load, max.     of the mules putting with resisting lead resur-	100 Hz
of the pulse outputs, with resistive load, max.  Table correct of the pulse to (a second).	2.5 kHz
Total current of the outputs (per group)	
horizontal installation	0.4
— up to 40 °C, max.	3 A
— up to 60 °C, max.	2 A
vertical installation	
— up to 40 °C, max.	2 A
Cable length	4.000
• shielded, max.	1 000 m
unshielded, max.	600 m
Analog inputs	
Number of analog inputs	
For voltage/current measurement	4
For resistance/resistance thermometer measurement	1
integrated channels (AI)	4+1
permissible input voltage for current input (destruction limit), max.	5 V; Permanent
permissible input voltage for voltage input (destruction limit), max.	30 V; Permanent
permissible input current for voltage input (destruction limit), max.	0.5 mA; Permanent
permissible input current for current input (destruction limit), max.	50 mA; Permanent
No-load voltage for resistance-type transmitter, typ.	2.5 V
Constant measurement current for resistance-type transmitter, typ.	1.8 to 3.3 mA
Technical unit for temperature measurement adjustable	Vac Dagraca Calaina / dagraca Fabranhait / Kalvin
Input ranges	Yes; Degrees Celsius / degrees Fahrenheit / Kelvin
	res, Degrees Ceisius / degrees Famenneit / Keivin
Current	Yes
<ul><li>Current</li><li>Resistance thermometer</li></ul>	
	Yes
Resistance thermometer	Yes Yes; Pt 100 / 10 MΩ
Resistance thermometer     Resistance	Yes Yes; Pt 100 / 10 MΩ
Resistance thermometer     Resistance Input ranges (rated values), voltages	Yes Yes; Pt 100 / 10 MΩ Yes
<ul> <li>Resistance thermometer</li> <li>Resistance</li> <li>Input ranges (rated values), voltages</li> <li>0 to +10 V</li> </ul>	Yes Yes; Pt 100 / 10 MΩ Yes
Resistance thermometer Resistance Input ranges (rated values), voltages  10 to +10 V Input resistance (0 to 10 V)	Yes Yes; Pt 100 / 10 MΩ Yes
Resistance thermometer Resistance Input ranges (rated values), voltages  o to +10 V — Input resistance (0 to 10 V) Input ranges (rated values), currents	Yes Yes; Pt 100 / 10 M $\Omega$ Yes Yes 100 k $\Omega$
Resistance thermometer Resistance Input ranges (rated values), voltages  o to +10 V — Input resistance (0 to 10 V) Input ranges (rated values), currents o to 20 mA	Yes Yes; Pt 100 / 10 M $\Omega$ Yes Yes 100 k $\Omega$
Resistance thermometer  Resistance Input ranges (rated values), voltages  o to +10 V  Input resistance (0 to 10 V)  Input ranges (rated values), currents  o to 20 mA  Input resistance (0 to 20 mA)	Yes Yes; Pt 100 / 10 M $\Omega$ Yes Yes 100 k $\Omega$
Resistance thermometer Resistance Input ranges (rated values), voltages  o to +10 V — Input resistance (0 to 10 V) Input ranges (rated values), currents  o to 20 mA — Input resistance (0 to 20 mA)  -20 mA to +20 mA	Yes Yes; Pt 100 / 10 M $\Omega$ Yes Yes 100 k $\Omega$

Input ranges (rated values), resistance thermometer	V
• Pt 100	Yes
— Input resistance (Pt 100)	10 ΜΩ
Input ranges (rated values), resistors	
• 0 to 600 ohms	Yes
— Input resistance (0 to 600 ohms)	10 ΜΩ
Thermocouple (TC)	
Temperature compensation	
— parameterizable	No
Characteristic linearization	
<ul> <li>parameterizable</li> </ul>	Yes; by software
— for resistance thermometer	Pt 100
Cable length	
<ul><li>shielded, max.</li></ul>	100 m
Analog outputs	
Number of analog outputs	2
integrated channels (AO)	2
Voltage output, short-circuit protection	Yes
Voltage output, short-circuit current, max.	55 mA
Current output, no-load voltage, max.	17 V
Output ranges, voltage	
O to 10 V	Yes
• -10 V to +10 V	Yes
	Tes
Output ranges, current	Vac
• 0 to 20 mA	Yes
• -20 mA to +20 mA	Yes
• 4 mA to 20 mA	Yes
Connection of actuators	
for voltage output two-wire connection	Yes; Without compensation of the line resistances
<ul> <li>for voltage output four-wire connection</li> </ul>	No
for current output two-wire connection	Yes
Load impedance (in rated range of output)	
<ul><li>with voltage outputs, min.</li></ul>	1 kΩ
<ul> <li>with voltage outputs, capacitive load, max.</li> </ul>	0.1 μF
<ul><li>with current outputs, max.</li></ul>	300 Ω
<ul> <li>with current outputs, inductive load, max.</li> </ul>	0.1 mH
Destruction limits against externally applied voltages and cur	rents
<ul> <li>Voltages at the outputs towards MANA</li> </ul>	16 V; Permanent
<ul> <li>Current, max.</li> </ul>	50 mA; Permanent
Cable length	
• shielded, max.	200 m
Analog value generation for the inputs	
Measurement principle	Actual value encryption (successive approximation)
Integration and conversion time/resolution per channel	, , , , , , , , , , , , , , , , , , , ,
Resolution with overrange (bit including sign), max.	12 bit
Integration time, parameterizable	Yes
permissible input frequency, max.	400 Hz
Time constant of the input filter	0.38 ms
Basic execution time of the module (all channels)	1 ms
released)	1 110
Analog value generation for the outputs	
Integration and conversion time/resolution per channel	
Resolution with overrange (bit including sign), max.	12 bit
Conversion time (per channel)	1 ms
Settling time	
for resistive load	0.6 ms
for capacitive load	1 ms
• for inductive load	0.5 ms
	0.0 1110

Encoder	
Connection of signal encoders	
for voltage measurement	Yes
<ul> <li>for current measurement as 2-wire transducer</li> </ul>	Yes; with external supply
• for current measurement as 4-wire transducer	Yes
for resistance measurement with two-wire connection	Yes; Without compensation of the line resistances
<ul> <li>for resistance measurement with three-wire connection</li> </ul>	No
<ul> <li>for resistance measurement with four-wire connection</li> </ul>	No
Connectable encoders	
2-wire sensor	Yes
<ul> <li>permissible quiescent current (2-wire sensor), max.</li> </ul>	1.5 mA
Errors/accuracies	
Temperature error (relative to input range), (+/-)	0.006 %/K
Crosstalk between the inputs, min.	60 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.06 %
Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-)	0.1 %
Linearity error (relative to output range), (+/-)	0.15 %
Temperature error (relative to output range), (+/-)	0.01 %/K
Crosstalk between the outputs, min.	60 dB
Repeat accuracy in steady state at 25 °C (relative to output range), (+/-)	0.06 %
Operational error limit in overall temperature range	
<ul> <li>Voltage, relative to input range, (+/-)</li> </ul>	1 %
<ul> <li>Current, relative to input range, (+/-)</li> </ul>	1 %
<ul> <li>Resistance, relative to input range, (+/-)</li> </ul>	5 %
<ul> <li>Voltage, relative to output range, (+/-)</li> </ul>	1 %
<ul> <li>Current, relative to output range, (+/-)</li> </ul>	1 %
Basic error limit (operational limit at 25 °C)	
<ul> <li>Voltage, relative to input range, (+/-)</li> </ul>	0.7 %; Linearity error ±0.06 %
<ul> <li>Current, relative to input range, (+/-)</li> </ul>	0.7 %; Linearity error ±0.06 %
<ul> <li>Resistance, relative to input range, (+/-)</li> </ul>	3 %; Linearity error ±0.2 %
<ul> <li>Resistance thermometer, relative to input range, (+/-)</li> </ul>	3 %
<ul> <li>Voltage, relative to output range, (+/-)</li> </ul>	0.7 %
<ul> <li>Current, relative to output range, (+/-)</li> </ul>	0.7 %
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =	interference frequency
<ul> <li>Series mode interference (peak value of interference &lt; rated value of input range), min.</li> </ul>	30 dB
<ul> <li>Common mode interference, min.</li> </ul>	40 dB
Interfaces	
Number of industrial Ethernet interfaces	0
Number of PROFINET interfaces	0
Number of RS 485 interfaces	2; MPI and PROFIBUS DP
Number of RS 422 interfaces	0
MPI  • Cable length, max.	50 m
	OU III
1. Interface	late was to d DO 405 interfer
Interface type	Integrated RS 485 interface
Isolated	No
Power supply to interface (15 to 30 V DC), max.	200 mA
Interface types	V
• RS 485	Yes
Protocols	V
• MPI	Yes

PROFINIO PR	N.
PROFIBUS DP master	No 
PROFIBUS DP slave	No 
Point-to-point connection	No
MPI	10
Number of connections	12
Transmission rate, max.	187.5 kbit/s
Services	V
— PG/OP communication	Yes
— Routing	Yes
Global data communication      S7 basic communication	Yes Yes
— S7 communication	Yes No
— S7 communication, as client	Yes
— S7 communication, as server	res
2. Interface	1.4
Interface type	Integrated RS 485 interface
Isolated	Yes
Power supply to interface (15 to 30 V DC), max.	200 mA
Interface types	V
• RS 485	Yes
Protocols	Nie
MPI     DESCRIPTION OF TAXABLE TO THE PROPERTY OF TAXABLE TO TAXABLE TAXABLE TO TAXABLE	No
PROFINET IO Controller	No
PROFINET CBA	No
PROFIBUS DP master	Yes
PROFIBUS DP slave	Yes
Point-to-point connection	No
PROFIBUS DP master	40: F PO/ODiti
Number of connections, max.  Transmission rate, may	12; For PG/OP communication
Transmission rate, max.      Number of DD players may	12 Mbit/s
Number of DP slaves, max.  Continue	32
Services  — PG/OP communication	Van
	Yes Yes
— Routing	
— Global data communication	No Vacul blacks only
— S7 basic communication	Yes; I blocks only
— S7 communication	Yes
— S7 communication, as client	No Yea
— S7 communication, as server	Yes
— Equidistance	Yes
— Isochronous mode	No You
<ul><li>— SYNC/FREEZE</li><li>— Activation/deactivation of DP slaves</li></ul>	Yes Yes
	Yes
<ul> <li>— Direct data exchange (slave-to-slave communication)</li> </ul>	1 00
— DPV1	Yes
Address area	
— Inputs, max.	1 kbyte
— Outputs, max.	1 kbyte
User data per DP slave	
— Inputs, max.	244 byte
— Outputs, max.	244 byte
PROFIBUS DP slave	
Number of connections	12
• GSD file	The latest GSD file is available at: http://www.siemens.com/profibus-gsd
Transmission rate, max.	12 Mbit/s
automatic baud rate search	Yes
Address area, max.	32

<ul> <li>User data per address area, max.</li> </ul>	32 byte
Services	
— PG/OP communication	Yes
— Routing	Yes; Only with active interface
<ul> <li>Global data communication</li> </ul>	No
<ul> <li>S7 basic communication</li> </ul>	No
— S7 communication	Yes
— S7 communication, as client	No
— S7 communication, as server	Yes
Direct data exchange (slave-to-slave)	Yes
communication)	163
— DPV1	No
Transfer memory	
— Inputs	244 byte
— Outputs	244 byte
Communication functions	Z++ byte
	V
PG/OP communication	Yes
Global data communication	
• supported	Yes
<ul> <li>Number of GD loops, max.</li> </ul>	4
<ul> <li>Number of GD packets, max.</li> </ul>	4
<ul> <li>Number of GD packets, transmitter, max.</li> </ul>	4
<ul> <li>Number of GD packets, receiver, max.</li> </ul>	4
<ul> <li>Size of GD packets, max.</li> </ul>	22 byte
<ul> <li>Size of GD packet (of which consistent), max.</li> </ul>	22 byte
S7 basic communication	
• supported	Yes
User data per job, max.	76 byte
<ul> <li>User data per job (of which consistent), max.</li> </ul>	76 byte; 76 bytes (with X_SEND or X_RCV); 64 bytes (with X_PUT or
	X_GET as server)
S7 communication	
<ul><li>supported</li></ul>	Yes
• as server	Yes
• as client	Yes; Via CP and loadable FB
User data per job, max.	180 kbyte; With PUT/GET
<ul> <li>User data per job (of which consistent), max.</li> </ul>	64 byte
	•
S5 compatible communication	Yes: via CP and loadable FC
S5 compatible communication • supported	Yes; via CP and loadable FC
S5 compatible communication  • supported  Number of connections	
S5 compatible communication	12
S5 compatible communication  • supported  Number of connections  • overall  • usable for PG communication	12 11
S5 compatible communication  • supported  Number of connections  • overall  • usable for PG communication  — reserved for PG communication	12 11 1
S5 compatible communication  • supported  Number of connections  • overall  • usable for PG communication  — reserved for PG communication  — adjustable for PG communication, min.	12 11 1
S5 compatible communication  • supported  Number of connections  • overall  • usable for PG communication  — reserved for PG communication  — adjustable for PG communication, min.  — adjustable for PG communication, max.	12 11 1 1 1
S5 compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication	12 11 1 1 11 11
S5 compatible communication  • supported  Number of connections  • overall  • usable for PG communication  — reserved for PG communication  — adjustable for PG communication, min.  — adjustable for PG communication, max.  • usable for OP communication  — reserved for OP communication	12 11 1 1 1
S5 compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication	12 11 1 1 11 11
S5 compatible communication  • supported  Number of connections  • overall  • usable for PG communication  — reserved for PG communication  — adjustable for PG communication, min.  — adjustable for PG communication, max.  • usable for OP communication  — reserved for OP communication	12 11 1 1 11 11
S5 compatible communication  • supported  Number of connections  • overall  • usable for PG communication  — reserved for PG communication  — adjustable for PG communication, min.  — adjustable for PG communication, max.  • usable for OP communication  — reserved for OP communication  — adjustable for OP communication  — adjustable for OP communication, min.	12 11 1 1 11 11 11
S5 compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication  adjustable for OP communication, min.  adjustable for OP communication, max.	12 11 1 1 1 1 1 1 1 1 1 1 1 1 1
St compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication  adjustable for OP communication, min.  adjustable for OP communication, max.  usable for S7 basic communication	12 11 1 1 1 1 1 1 1 1 1 1 1 8
S5 compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication, min.  adjustable for OP communication, min.  adjustable for OP communication, max.  usable for S7 basic communication  reserved for S7 basic communication  adjustable for S7 basic communication, min.	12 11 1 1 1 1 1 1 1 1 1 1 1 1 1 0
S5 compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication  adjustable for OP communication, min.  adjustable for OP communication, max.  usable for S7 basic communication  reserved for S7 basic communication  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, min.	12 11 1 1 1 1 1 1 1 1 1 1 1 0 0 0 0 8
St compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication  adjustable for OP communication, min.  adjustable for OP communication, max.  usable for S7 basic communication  reserved for S7 basic communication  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, min.  usable for routing	12 11 1 1 1 1 1 1 1 1 1 1 0 0 0
S5 compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication  adjustable for OP communication, min.  adjustable for OP communication, max.  usable for S7 basic communication  reserved for S7 basic communication  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, min.	12 11 1 1 1 11 11 11 11 11 18 0 0 0 8 4; max.
Stocompatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication  adjustable for OP communication, min.  adjustable for OP communication, max.  usable for S7 basic communication  reserved for S7 basic communication  adjustable for S7 basic communication  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, max.  usable for routing  message functions  Number of login stations for message functions, max.	12 11 1 1 1 11 11 11 11 11 18 0 0 0 8 4; max.
St compatible communication  supported  Number of connections  overall  usable for PG communication  reserved for PG communication  adjustable for PG communication, min.  adjustable for PG communication, max.  usable for OP communication  reserved for OP communication  adjustable for OP communication  adjustable for OP communication, min.  adjustable for OP communication, max.  usable for S7 basic communication  reserved for S7 basic communication  adjustable for S7 basic communication  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, min.  adjustable for S7 basic communication, max.  usable for routing	12 11 1 1 1 11 11 11 11 18 0 0 0 8 4; max.

	Vac
Status block	Yes
Single step	Yes
Number of breakpoints	2
Status/control	Van
Status/control variable	Yes
• Variables	Inputs, outputs, memory bits, DB, times, counters
<ul> <li>Number of variables, max.</li> </ul>	30
<ul><li>of which status variables, max.</li></ul>	30
— of which control variables, max.	14
Forcing	
<ul><li>Forcing</li></ul>	Yes
<ul><li>Forcing, variables</li></ul>	Inputs, outputs
Number of variables, max.	10
Diagnostic buffer	
• present	Yes
Number of entries, max.	100
Interrupts/diagnostics/status information	
Diagnostics indication LED	
<ul> <li>Status indicator digital input (green)</li> </ul>	Yes
<ul> <li>Status indicator digital output (green)</li> </ul>	Yes
Integrated Functions	
Number of counters	4; See "Technological Functions" manual
Counting frequency (counter) max.	60 kHz
Frequency measurement	Yes
Number of frequency meters	4; up to 60 kHz (see "Technological Functions" manual)
controlled positioning	Yes
integrated function blocks (closed-loop control)	PID controller (see "Technological Functions" manual)
PID controller	Yes
Number of pulse outputs	4; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual)
Limit frequency (pulse)	2.5 kHz
Potential separation	
Potential separation digital inputs	
Potential separation digital inputs	Yes
between the channels	No
between the channels and backplane bus	Yes
Potential separation digital outputs	
	Yes
Potential separation digital outputs	Yes
<ul><li>Potential separation digital outputs</li><li>between the channels</li></ul>	Yes
<ul><li>Potential separation digital outputs</li><li>between the channels</li><li>between the channels, in groups of</li></ul>	Yes 8
<ul> <li>Potential separation digital outputs</li> <li>between the channels</li> <li>between the channels, in groups of</li> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>Potential separation digital outputs</li> <li>between the channels</li> <li>between the channels, in groups of</li> <li>between the channels and backplane bus</li> </ul> Potential separation analog inputs	Yes 8 Yes
<ul> <li>Potential separation digital outputs</li> <li>between the channels</li> <li>between the channels, in groups of</li> <li>between the channels and backplane bus</li> </ul> Potential separation analog inputs <ul> <li>Potential separation analog inputs</li> </ul>	Yes 8 Yes Yes; common for analog I/O
<ul> <li>Potential separation digital outputs</li> <li>between the channels</li> <li>between the channels, in groups of</li> <li>between the channels and backplane bus</li> </ul> Potential separation analog inputs <ul> <li>Potential separation analog inputs</li> <li>between the channels</li> </ul>	Yes 8 Yes Yes; common for analog I/O No
<ul> <li>Potential separation digital outputs</li> <li>between the channels</li> <li>between the channels, in groups of</li> <li>between the channels and backplane bus</li> </ul> Potential separation analog inputs <ul> <li>Potential separation analog inputs</li> <li>between the channels</li> <li>between the channels and backplane bus</li> </ul>	Yes 8 Yes Yes; common for analog I/O
<ul> <li>Potential separation digital outputs</li> <li>between the channels</li> <li>between the channels, in groups of</li> <li>between the channels and backplane bus</li> </ul> Potential separation analog inputs <ul> <li>Potential separation analog inputs</li> <li>between the channels</li> <li>between the channels and backplane bus</li> </ul> Potential separation analog outputs	Yes 8 Yes  Yes; common for analog I/O No Yes
<ul> <li>Potential separation digital outputs</li> <li>between the channels</li> <li>between the channels, in groups of</li> <li>between the channels and backplane bus</li> <li>Potential separation analog inputs</li> <li>Potential separation analog inputs</li> <li>between the channels</li> <li>between the channels and backplane bus</li> <li>Potential separation analog outputs</li> <li>Potential separation analog outputs</li> </ul>	Yes 8 Yes: Yes; common for analog I/O No Yes  Yes; common for analog I/O
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs between the channels	Yes 8 Yes  Yes; common for analog I/O No Yes  Yes; common for analog I/O No
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs between the channels between the channels between the channels	Yes 8 Yes: Yes; common for analog I/O No Yes  Yes; common for analog I/O
Potential separation digital outputs  between the channels  between the channels, in groups of  between the channels and backplane bus  Potential separation analog inputs  Potential separation analog inputs  between the channels  between the channels and backplane bus  Potential separation analog outputs  Potential separation analog outputs  Potential separation analog outputs  between the channels  between the channels  between the channels and backplane bus	Yes 8 Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs Potential separation analog outputs between the channels between the channels between the channels and backplane bus  Isolation Isolation tested with	Yes 8 Yes  Yes; common for analog I/O No Yes  Yes; common for analog I/O No
Potential separation digital outputs between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs Potential separation analog outputs between the channels between the channels between the channels and backplane bus  Isolation  Isolation  Isolation	Yes 8 Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs between the channels between the channels between the channels between the channels configuration  Isolation Configuration	Yes 8 Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes  600 V DC
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs between the channels between the channels between the channels between the channels Configuration  Configuration  Configuration software STEP 7	Yes 8 Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs Potential separation analog outputs between the channels between the channels between the channels Steven the channels and backplane bus  Isolation  Isolation  Configuration  Configuration software STEP 7  Programming	Yes 8 Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes  600 V DC  Yes; V5.3 SP2 with HW update
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs  Potential separation analog inputs between the channels between the channels and backplane bus  Potential separation analog outputs  Potential separation analog outputs  Potential separation analog outputs  between the channels between the channels between the channels  Steven the channels and backplane bus  Isolation  Isolation  Configuration  Configuration software  STEP 7  Programming Command set	Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes  600 V DC  Yes; V5.3 SP2 with HW update  see instruction list
Potential separation digital outputs between the channels between the channels, in groups of between the channels and backplane bus  Potential separation analog inputs Potential separation analog inputs between the channels between the channels and backplane bus  Potential separation analog outputs Potential separation analog outputs Potential separation analog outputs between the channels between the channels between the channels Steven the channels and backplane bus  Isolation  Isolation  Configuration  Configuration software STEP 7  Programming	Yes 8 Yes; common for analog I/O No Yes  Yes; common for analog I/O No Yes  600 V DC  Yes; V5.3 SP2 with HW update

<ul> <li>System function blocks (SFB)</li> </ul>	see instruction list
Programming language	
— LAD	Yes
— FBD	Yes
— STL	Yes
— SCL	Yes
— CFC	Yes
— GRAPH	Yes
— HiGraph®	Yes
Know-how protection	
<ul> <li>User program protection/password protection</li> </ul>	Yes
Dimensions	
Width	120 mm
Height	125 mm
Depth	130 mm
Weights	
Weight, approx.	676 g

1/16/2021 🖸

last modified: