SIEMENS

Data sheet for SINAMICS Power module PM240P-2

Article No.: 6SL3210-1RH31-4UL0

Client order no. : Order no. : Offer no. : Remarks :





Figure simil

Rated data		
Input		
Number of phases	3 AC	
Line voltage	500 690 V ±1	10 %
Line frequency	47 63 Hz	
Rated current (LO)	137.00 A	
Rated current (HO)	122.00 A	
Output		
Number of phases	3 AC	
Rated voltage	690V IEC	600V NEC 1)
Rated power (LO)	132.00 kW	125.00 hp
Rated power (HO)	110.00 kW	100.00 hp
Rated current (LO)	142.00 A	
Rated current (HO)	115.00 A	
Max. output current	192.00 A	
Pulse frequency	2 kHz	
Output frequency for vector control	0 200 Hz	
Output frequency for V/f control	0 550 Hz	
Overload capability		

	Overioad	capabi	iity
--	----------	--------	------

Low Overload (LO)

 $1.1\,x$ rated output current (i.e. 110 % overload) for 57 s with a cycle time of 300 s 1.35 \times rated output current (i.e. 135 % overload) for 3 s with a cycle time of 300 s

High Overload (HO)

 $1.5\times output$ current rating (i.e., 150 % overload) for 60 s with a cycle time of 300 s

General tech. specifications		
Power factor λ	0.90	
Offset factor $\cos\phi$	0.99	
Efficiency η	0.99	
Sound pressure level (1m)	68 dB	
Power loss	2.49 kW	
Filter class (integrated)	-	


Ambient conditions		
Internal air cooling		
0.153 m³/s (5.403 ft³/s)		
1,000 m (3,280.84 ft)		
-20 40 °C (-4 104 °F)		
-20 50 °C (-4 122 °F)		
-40 70 °C (-40 158 °F)		
-40 70 °C (-40 158 °F)		
95 % RH, condensation not permitted		
ections		
M10 bolt		
35.00 120.00 mm ² (AWG 2 AWG -3)		
M10 bolt		
35.00 120.00 mm ² (AWG 2 AWG -3)		
300 m (984.25 ft)		
450 m (1,476.38 ft)		
ical data		
IP20 / UL open type		
FSF		
60.00 kg (132.28 lb)		
305 mm (12.01 in)		
708 mm (27.87 in)		
357 mm (14.06 in)		
Standards		
UL, cUL, CE, SEMI F47		



Data sheet for SINAMICS Power module PM240P-2

Article No.: 6SL3210-1RH31-4UL0

Converter losses to IEC61800-9-2*	
Efficiency class	IE2
Comparison with the reference converter (90% / 100%)	35.60 %



The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency (f). The values are valid for the basic version of the converter without options/components.

*converted values

¹⁾ The output current and HP ratings are valid for the voltage range 550V-600V