

variable speed drive ATV31 - 7.5kW - 500V 3-phase supply - EMC filter -**IP20**

ATV31HU75N4

Discontinued on: 31 December 2011

• End-of-service on: 31 December 2015

Main

Product or component type Product specific application Simple machine Component name ATV31 Assembly style With heat sink EMC filter Integrated [Us] rated supply voltage 380500 V - 55 % Supply frequency 5060 Hz - 55 % Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V - 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal		
Product specific application Simple machine Component name ATV31 Assembly style With heat sink EMC filter Integrated [Us] rated supply voltage 380500 V - 55 % Supply frequency 5060 Hz - 55 % Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Range of product	Altivar
Component name ATV31 Assembly style With heat sink EMC filter Integrated [Us] rated supply voltage 380500 V - 55 % Supply frequency 5060 Hz - 55 % Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Product or component type	Variable speed drive
Assembly style With heat sink EMC filter Integrated [Us] rated supply voltage 380500 V - 55 % Supply frequency 5060 Hz - 55 % Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Product specific application	Simple machine
EMC filter Integrated [Us] rated supply voltage 380500 V - 55 % Supply frequency 5060 Hz - 55 % Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Component name	ATV31
Supply frequency 5060 Hz - 55 % Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Assembly style	With heat sink
Supply frequency 5060 Hz - 55 % Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	EMC filter	Integrated
Network number of phases 3 phases Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	[Us] rated supply voltage	380500 V - 55 %
Motor power kW 7.5 kW 4 kHz Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Supply frequency	5060 Hz - 55 %
Motor power hp 10 hp 4 kHz Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Sensorless flux vector control with PWM type motor control signal	Network number of phases	3 phases
Line current 21 A at 500 V 27.7 A at 380 V, Isc = 1 kA Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Motor power kW	7.5 kW 4 kHz
Apparent power 18 kVA Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Motor power hp	10 hp 4 kHz
Prospective line Isc 1 kA Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Line current	
Nominal output current 17 A 4 kHz Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Apparent power	18 kVA
Maximum transient current 25.5 A for 60 s Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Prospective line Isc	1 kA
Power dissipation in W 269 W at nominal load Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Nominal output current	17 A 4 kHz
Asynchronous motor control Sensorless flux vector control with PWM type motor control signal	Maximum transient current	25.5 A for 60 s
	Power dissipation in W	269 W at nominal load
	Asynchronous motor control profile	

Complementary

Analogue input number

Product destination	Asynchronous motors
Supply voltage limits	323550 V
Network frequency	47.563 Hz
Output frequency	0.00050.5 kHz
Nominal switching frequency	4 kHz
Switching frequency	216 kHz adjustable

Speed range	150
Transient overtorque	150170 % of nominal motor torque
Braking torque	<= 150 % during 60 s with braking resistor 100 % with braking resistor continuously 150 % without braking resistor
Regulation loop	Frequency PI regulator
Motor slip compensation	Automatic whatever the load Adjustable Suppressable
Output voltage	<= power supply voltage
Electrical connection	Al1, Al2, Al3, AOV, AOC, R1A, R1B, R1C, R2A, R2B, Ll1Ll6 terminal 2.5 mm² AWG 14 L1, L2, L3, U, V, W, PA, PB, PA/+, PC/- terminal 2.5 mm² AWG 14
Tightening torque	Al1, Al2, Al3, AOV, AOC, R1A, R1B, R1C, R2A, R2B, LI1LI6: 0.6 N.m L1, L2, L3, U, V, W, PA, PB, PA/+, PC/-: 0.8 N.m
Insulation	Electrical between power and control
Supply	Internal supply for logic inputs: 1930 V 100 mA, protection type: overload and short-circuit protection Internal supply for reference potentiometer (2.2 to 10 kOhm): 1010.8 V 10 mA, protection type: overload and short-circuit protection
Analogue input type	Al3 configurable current 020 mA, impedance: 250 Ohm Al1 configurable voltage 010 V, input voltage 30 V max, impedance: 30000 Ohm Al2 configurable voltage +/- 10 V, input voltage 30 V max, impedance: 30000 Ohm
Sampling duration	LI1LI6: 4 ms discrete AI1, AI2, AI3: 8 ms analog
Response time	AOV, AOC 8 ms for analog R1A, R1B, R1C, R2A, R2B 8 ms for discrete
Linearity error	+/- 0.2 % for output
Analogue output number	2
Analogue output type	AOC configurable current: 020 mA, impedance: 800 Ohm, resolution: 8 bits AOV configurable voltage: 010 V, impedance: 470 Ohm, resolution: 8 bits
Discrete input logic	Positive logic (source) (LI1LI6), < 5 V (state 0), > 11 V (state 1) Logic input not wired (LI1LI4), < 13 V (state 1) Negative logic (source) (LI1LI6), > 19 V (state 0)
Discrete output number	2
Discrete output type	Configurable relay logic: (R1A, R1B, R1C) 1 NO + 1 NC - 100000 cycles Configurable relay logic: (R2A, R2B) NC - 100000 cycles
Minimum switching current	R1-R2 10 mA at 5 V DC
Maximum switching current	R1-R2: 2 A at 250 V AC inductive load, cos phi = 0.4 and L/R = 7 ms R1-R2: 2 A at 30 V DC inductive load, cos phi = 0.4 and L/R = 7 ms R1-R2: 5 A at 250 V AC resistive load, cos phi = 1 and L/R = 0 ms R1-R2: 5 A at 30 V DC resistive load, cos phi = 1 and L/R = 0 ms
Discrete input number	6
Discrete input type	(LI1LI6) programmable at 24 V, 0100 mA for PLC, impedance: 3500 Ohm
Acceleration and deceleration ramps	S, U or customized Linear adjustable separately from 0.1 to 999.9 s
Braking to standstill	By DC injection
Protection type	Input phase breaks: drive Line supply overvoltage and undervoltage safety circuits: drive Line supply phase loss safety function, for three phases supply: drive Motor phase breaks: drive Overcurrent between output phases and earth (on power up only): drive Overheating protection: drive Short-circuit between motor phases: drive Thermal protection: motor
Insulation resistance	>= 500 mOhm 500 V DC for 1 minute
Display type	1 LED (red) for drive voltage Four 7-segment display units for CANopen bus status
Time constant	5 ms for reference change
Frequency resolution	Display unit: 0.1 Hz Analog input: 0.1100 Hz

Connector type	1 RJ45 for CANopen via VW3 CANTAP2 adaptor 1 RJ45 for Modbus
Physical interface	RS485 multidrop serial link for CANopen via VW3 CANTAP2 adaptor RS485 multidrop serial link for Modbus
Transmission frame	RTU for CANopen via VW3 CANTAP2 adaptor RTU for Modbus
Transmission rate	10, 20, 50, 125, 250, 500 kbps or 1 Mbps for CANopen via VW3 CANTAP2 adaptor 4800, 9600 or 19200 bps for Modbus
Number of addresses	1127 for CANopen via VW3 CANTAP2 adaptor 1247 for Modbus
Number of drive	127 for CANopen via VW3 CANTAP2 adaptor 31 for Modbus
Marking	CE
Operating position	Vertical +/- 10 degree
Outer dimension	232 x 180 x 170 mm 405 x 234 x 268 mm 300 x 210 x 170 mm
Product weight	6.5 kg
Environment	
Dielectric strength	2410 V DC between earth and power terminals 3400 V AC between control and power terminals
Electromagnetic compatibility	1.2/50 µs - 8/20 µs surge immunity test level 3 conforming to IEC 61000-4-5 Electrical fast transient/burst immunity test level 4 conforming to IEC 61000-4-4 Electrostatic discharge immunity test level 3 conforming to IEC 61000-4-2 Radiated radio-frequency electromagnetic field immunity test level 3 conforming to IEC 61000-4-3
Standards	EN 50178
Product certifications	UL CSA C-Tick N998
IP degree of protection	On upper part: IP20 (without cover plate) On connection terminals: IP21 On upper part: IP31 On upper part: IP41
Pollution degree	2
Protective treatment	TC
Vibration resistance	1 gn (f= 13150 Hz) conforming to EN/IEC 60068-2-6 1.5 mm (f= 313 Hz) conforming to EN/IEC 60068-2-6
Shock resistance	15 gn for 11 ms conforming to EN/IEC 60068-2-27
Relative humidity	595 % without condensation conforming to IEC 60068-2-3 595 % without dripping water conforming to IEC 60068-2-3
Ambient air temperature for	
storage	-2570 °C
-	-2570 °C -1050 °C without derating (with protective cover on top of the drive) -1060 °C with derating factor (without protective cover on top of the drive)
storage Ambient air temperature for	-1050 °C without derating (with protective cover on top of the drive)
Ambient air temperature for operation	-1050 °C without derating (with protective cover on top of the drive) -1060 °C with derating factor (without protective cover on top of the drive) <= 1000 m without derating

Recommended replacement(s)

ATV31HU75N4 is replaced by:

1x



Variable speed drive, Altivar Machine ATV320, 7.5 kW, 380...500 V, 3 phases, book ATV320U75N4B