

Plain Text Display Terminal - 128 x 64 pixels - IP21

VW3A1113

EAN Code: 3606480702228

Main

Range of product	Altivar	
Range compatibility	Easy Altivar 610 Altivar Machine ATV340	
Accessory / separate part category	Display and signalling accessories	
Accessory / separate part type	Display terminal	
Accessory / separate part destination	Variable speed drive	
Product specific application	To control, adjust and configure the drive To display the current values To save and download configurations	
IP degree of protection	IP21	

Complementary

User language	French German English Spanish Italian Chinese
Realtime clock	Without
Display type	Backlit LCD screen white
Messages display capacity	2 lines
Pixel resolution	128 x 64
Net weight	0.05 kg

Environment

Ambient air temperature for operation -15...50 °C

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5.700 cm
Package 1 Width	9.200 cm
Package 1 Length	12.400 cm
Package 1 Weight	99.000 g
Unit Type of Package 2	S03

Number of Units in Package 2	45
Package 2 Height	30.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	5.360 kg

Contractual warranty

Warranty 18 months

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

How this information helps you >

⊘ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	51
Environmental Disclosure	Product Environmental Profile

Use Better

Packaging made with recycled cardboard	No
Packaging without single use plastic	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	1e93978f-15df-45bb- af19-570d1473ed50
REACh Regulation	REACh Declaration
China RoHS Regulation	China RoHS declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations

Take-back

No